

L83 MK2+L83S MK2 Column System

L83 MK2+L83S MK2 system is a compact multi-purpose active DSP column system consisting of a passive full-range column speaker L83 MK2 and an active DSP controlled dual 12" subwoofer L83S MK2.

L83 MK2 passive full-range column speaker is with 8pcs 3" full-range drivers and 2pcs 1" customized drivers. The drivers are designed with sophisticated measurement and arranged elaborately by physical calibration technology Phycal[™] to improve vertical acoustic beam coverage. The ETE[™] waveguide system developed by Audiocenter forms cylindrical wave, then couples continually, working together with customized horn design to realize the perfect joint of frequency response, which provides the accurate horizontal coverage and ensures the well-balanced, clean and clear sound. L83 MK2 can meet the reinforcement application in different venues and complex space.

L83S MK2 is an active DSP controlled compact subwoofer with 2pcs 12" customized drivers and Class D amplifier module. The system works efficiently and has built-in Bluetooth that supports multiple signal inputs.

L83S MK2 has been carefully tested. With elaborate acoustic design, innovative FTF™ LF driver design and extensive testing, the cabinet is with three-order band-pass filter. By coupling the system continually and overlaying the resonances, the LF efficiency is improved significantly.

L83 MK2+L83S MK2 is a plug and play column system with easy set up. The presets are made with a lot of testing. The system can be put in various applications.











SPECIFICATION

Type Frequency Response(-10dB) Horizontal Coverage Vertical Coverage Maximum Calculated SPL/1M(Continuous/Peak): HF LF Subwoofer DSP	Active I 40Hz-2 110° 129dB/ Custom Custom Custom
Processor	96kHz
Presets	L83 MK
Class D amplifier	
Power(RMS standards)	2000W
Peak Power	4000W
Frequency Response	20Hz-2
Intermodulation Distortion	<0.05%
Total Harmonic Distortion	<0.05%
Cooling System	Cooling
Protection	DC prot protecti overloa overvol
Signal Input	Combo Stereo
Signal Output	Male XI
Amplifier Output Link L83 MK2	Speako
Column Input Link L83S MK2	Speako
Power Input	IEC pov
AC Power Opera ting Range	100V-1
Power consumption (1/8 output power)	167W
CABINET	0110
Cabinet Material Cabinet Color Grille	CNC m Black is for cust Iron me
Handles	L83S N
L83S MK2 Pole Mount	M20 ba
Speaker Dimension(W×H×D)	405.40
L83 MK2 L83S MK2	135×12 374×69
Carton Dimensions (W×H×D)	374×08
L83 MK2	1302×2
L83S MK2	467×62
Net Weight	407 ×02
L83 MK2	10.5kg
L83S MK2	34.0kg
Shipping Weight	eng
L83 MK2	14.0kg
L83S MK2	38.0kg
	- 3

DSP-controlled Column Speaker System -20kHz B/135dB omized driver, 2pcs 1" drivers omized driver, 8pcs 3" drivers mized driver, 2pcs 12" driver z signal sampling frequency IK2, L65 MK2, T4L N W -20kHz(±0.5dB) 5% 5% ng with fans, air convection rotection, short circuit protection, overheat ction, input overload protection, output bad protection, soft startup protection, oltage protection, undervoltage protection oo (female XLR & Mono jack 6.35), o Bluetooth XLR kon 4pin kon 4pin ower connector -130V~ or 220V-240V~ (±10%,50/60Hz) made of excellent wood is the default color. Contact Audiocenter stomization nesh MK2 2 side oase Φ35mm 200×165mm 690×538mm <229×220mm 625×780mm



BACK PANEL

690





ACCESSORIES



Hand bag For 2 pcs L83 MK2



L83S MK2 Protection bag (with wheel)